



P1000S

UPI & QR **PAYMENTS**



TICKETING



PARKING





STORE BILLING & INVENTORY



PAY ON DELIVERY



HoReCa



Cloud Based MDM

Location & Geo-fencing

Device _ Management

TMS & KMS



System Management

— App Store


OTA Update



























SPECIFICATIONS - P1000S

SPECIFICATIONS	- 10003
P1000S	Mobile or Desktop use
	5-inch Colour Display
	Multiple communications
	High speed thermal printer
	Contactless NFC Card Reader
Processor	Quad-core Cortex A7
os	Android 9 with GMS
Memory	1GB RAM, 8GB ROM
Display	5.0-inch colour display, 1280 x 720 pixels resolution
Keypad	1 x ON/OFF
Camera	2MP rear camera with flash (Optional 5MP)
Printer	2-inch high speed thermal printer, paper roll:58mm*40mm
Card Readers	Contactless NFC Card Reader
Card Slots	1xSIM + 2xSAM card slots
	(Optional 2xSIM + 1xSAM card slots)
Communications	4G/3G/2G, Bluetooth, BLE, Wi-Fi
Audio	Speaker
Battery	7.4V 2000 mAh, rechargeable Li-ion battery
	(Optional 3100 mAh large battery)
Adapter (Included)	Input: 100~240V AC 50/60Hz; Output: 5.0V DC, 2.0A
Peripheral Ports	1x Micro USB2.0, 1x DC JACK, 1x Micro-SD
Certifications	CE, RoHS, FCC, BIS
Charging Base	1x DC 3.5mm Port (POGO), 1x LED Power Indicator
(Optional Accessory)	ix De 3.511111 Fort (FOGO), ix LED Fower indicator
Multi-Function Docking Base (Optional Accessory)	Scanner window, 2x Type-A HOST USB 2.0, 1x RJ45 (Serial port), 1x
	RJ45 (LAN), 1x DC 3.5mm Port (POGO), 1x LED Power Indicator, 1x LED
	communication Indicator











